

WAN FRAME RELAY

Configuraciones de las interfaces

Router0

```
int fa0/0
ip add 192.168.10.1 255.255.255.0
no shutdown
exit
int s0/0/0
ip add 10.10.10.1 255.255.255.252
clock rate 64000
no shutdown
```

Router1

```
int fa0/0
ip add 192.168.20.1 255.255.255.0
no shutdown
exit
int s0/0/0
ip add 10.10.10.2 255.255.255.252
no shutdown
```

Encapsulaciones FRAME RELAY

Enrutamiento RIP v2

Router0

```
int s0/0/0
encapsulation frame-relay
bandwidth 64
frame-relay map ip 10.10.10.2 102 broadcast
router rip
network 192.168.10.1
network 10.10.10.1
```

Router1

```
int s0/0/0
encapsulation frame-relay
bandwidth 64
frame-relay map ip 10.10.10.1 34 broadcast
router rip
network 192.168.20.1
network 10.10.10.2
```

CONFIGURACION DE FRAME RELAY EN LA NUBE

Cloud0

Physical Config

GLOBAL

Settings

TV Settings

CONNECTIONS

Frame Relay

DSL

Cable

INTERFACE

Serial0

Serial1

Serial2

Serial3

Modem4

Modem5

Ethernet6

Coaxial7

Frame Relay: Serial0

Port Status On

LMI

DLCI Name

DLCI	Name
102	R1

Cloud0

Physical Config

GLOBAL

Settings

TV Settings

CONNECTIONS

Frame Relay

DSL

Cable

INTERFACE

Serial0

Serial1

Serial2

Serial3

Modem4

Modem5

Ethernet6

Coaxial7

Frame Relay: Serial1

Port Status On

LMI

DLCI Name

DLCI	Name
34	R2

